



CSP-Dv Seismic Energy Source



The CSP-Dv is built on the proven high voltage technology of the industry leading CSP range of power supplies. Incorporating microprocessor control and configuration for greater configuration flexibility and reliability whilst retaining a fail-safe logic design.

The CSP-Dv adds to the standard safety systems and operational functions found across the entire range of CSP energy sources.

The CSP-Dv is compatible with the Applied Acoustics' S-Boom, single plate boomer and Squid sparker systems.

Key Features

- Microprocessor configuration and control.
- Intuitive user interface, with LCD display and LED indicators.
- Enhanced operator system feedback
- User programmable 'soft start'
- Master / Slave Key Support
- Additional safety/protection features
- Programmable voltage technology allows operator tuning to suit application
- All settings externally selectable
- High current and voltage solid state (semi-conductor) discharge method
- Debug log and diagnostics.
- Meets EC emissions regulations enabling interference-free field use
- Supplied in robust transit case, with HV junction box (HVJ3001) and mains lead.

Technical Specification

PHYSICAL

Size	Transit Case (7U) with cover in place and handles flat: 50cm(H) x 58cm(W) x 74cm(D)	
Weight	CSP-Dv700, case and cover: 60.5kg	CSP-Dv1200, case and cover: 61.5kg
	CSP-Dv2400, case and cover: 63.5kg	

ELECTRICAL SPECIFICATION

Mains Input	240VAC 45-65Hz@ 5.0kVA single phase. 3 pin connector Variable Input Power Circuitry (AVIP) 'soft start' circuitry
Voltage Output	2500 to 3950Vdc, 4 pin interlocked connector Solid state semi-conductor discharge method



CSP-Dv Technical Specification

Output Energy	Easy switch selectable in increments	
	CSP-Dv700	50,100,150,200,250,300,350,400,500,600,700 Joules
	CSP-Dv1200	50,100,150,200,250,300,350,400,450,500,550,600 700,800,900,1000,1100,1200 Joules
	CSP-Dv2400	50,100,150,200,250,300,400,500,600,700,750,800, 900,1000,1250,1500,1750,2000,2250,2400 Joules
Charging Rate	1500J/second for continuous operation at 0-45°C	
Capacitance	CSP-Dv700 112μF, 10 ⁸ shot life CSP-Dv1200 208μF, 10 ⁸ shot life CSP-Dv2400 304μF, 10 ⁸ shot life	
Trigger	User configured: External: +ve key (5-25VDC), -ve key or isolated closure Internal: +ve key (5-25VDC), -ve key Opto isolated BNC connector on front panel and remote box (optional)	
Repetition rate	User configured: External: 6pps maximum Internal: 166ms to 60seconds Limited by charge rate, energy level and sound source rating	
Earth	M8 stainless steel stud on front panel	

SAFETY FEATURES

Main microprocessor control circuits with fail-safe layer of logic circuitry
LCD display with system status information, configuration
Specially designed HV connector with interlock
High speed dump resistors for high voltage components
Capacitor bleed resistors
HV output open circuit shutdown
Trigger monitoring with time out and over clock shutdown
HV output current monitor and shutdown
Supply voltage monitoring and shutdown
High voltage monitoring
Over temperature shutdown
Cover and connector interlocks
Diagnostic log download for improved support
Intelligent remote control available to configure, trigger and operate remotely

The unit's internal design has a modular construction for ease of servicing and capacitor replacement. However, for safety reasons, only Applied Acoustics' trained engineers should attempt a repair.

COMPATIBLE SOUND SOURCES

CSP-Dv700, CSP-Dv1200	Squid 501, Squid 2000, Delta Sparker
CSP-Dv2400	AA201, AA251 and AA301 Boomer plates S-Boom System



Due to continual product improvement, specification information may be subject to change without notice.
CSP-Dv Seismic Energy Source/Feb 2016
©Applied Acoustic Engineering Ltd.



Applied Acoustic Engineering Ltd
Marine House, Marine Park
Gapton Hall Road
Great Yarmouth NR31 0NB
United Kingdom

T +44(0)1493 440355
F +44(0)1493 440720
E general@appliedacoustics.com
W www.appliedacoustics.com